

## Technical Notification

Document number: 95-133599

Date: April – 2011

### New software ver. 1.11 for the TT-3672A and the TT-3672B Thrane IP Handset.

**Subject:**

Please be informed that a new software version 1.11 for the Thrane IP Handset has been released.

**Priority:**

- **MEDIUM:** It is recommended to apply this change / initiative to all units in stock. For units sold it is recommended to apply this change / initiative next time the system(s) is inspected.

**Changes from SW version 1.10 to 1.11:**

- **New features**

- **Improvements**

- Faster updating of the handset during system power up.

- **User related bug fixes**

- Sending DTMS-tones, during user call termination, puts terminal DSP in wrong state. Fixed.

- **Known problem**

**Action:**

Download file **IP Handset ver\_111.zip** located at the Thrane & Thrane A/S eSupport Download Centre:


<http://extranet.thrane.com/Support/Technical%20Support.aspx>

Save / extract it on your hard disk.


The following will describe the procedure for installing IP handset software ver.

1.11 using a SAILOR 500/250/150, EXPLORER 325/727, or a switch with PPPOE (D-Link DES-1008P).


1. Make sure the SAILOR or EXPLORER Terminal is switched on and connected to your PC with an Ethernet cable. Or connect IP handset and pc to a switch with PPPOE ( in that case the network settings has to be manually inserted)
2. Make sure that the IP handset is connected to the terminal or to the switch
3. If using a terminal. Open your web-browser and open the Web Interface of the IP Handset. The IP address can be founding the Handset menu **Status** ➔ **Network information**. If using a switch. Use the static IP just inserted in the handset.
4. Select **UPLOAD FIRMWARE**.




5. Select **Browse...** then locate and select the software file **TT3672b\_1\_11\_1291.bin** stored and extracted to your hard drive.




6. Choose **Upload Firmware** and verify that the upload is in progress as shown below (status bar enabled in browser).




7. When the software has been uploaded to the IP Handset, the installation of the software will take place.




The IP Handset display will also show the progress of the installation.



8. When the installation is done, the IP Handset will restart.



9. After the restart of the IP Handset the new software version will be indicated as **1.11.1291**



10. End of updating procedure.

Thrane & Thrane  
After Sales Service

Author:	Date:	Checked:	Date:	Approved:	Date:
OCN	04-04-2011	JL	04-04-2011	GUJ	04-04-2011